

# Re:source M37 audio server

## Firmware Update – Cover Art

All Re:source M37 MKII (serial number 2000 or higher) can easily be updated to the latest firmware version.

Please note that the update can only be effected via the device, not via the web interface.

Use the button „Menu“ on the front of the M37 and select the setting menu by selecting the softkey button „setup“. Navigate upwards until you reach the menu “Online Update“. Choose this menu by selecting „OK“. Confirm the search for a new firmware version now. In case there is a more recent firmware version available, the download must be confirmed.

Straight after the download begins. After completion the M37 shuts down and boots up again. During this process the M37 may not be taken away from the net.

### Important advice:

Before updating it is important that the M37 has been working in the DHCP mode and not with a static IP address. In some cases the firmware update might not be working when it comes to a statically given IP address. In this case the M37 needs to be sent back to the factory.

## Update of the data base

The new firmware makes it not only for new albums possible to add a cover picture; it is also possible to add one to an existing album. However, it cannot be guaranteed that a picture can be found actually. For CDs which have been recorded directly on the M37 it is realistic that the cover can be found even retroactively. For music which has been played to the M37 via the Import folder the covers generally cannot be found.

As soon as the M37 has installed the new firmware (3.0.1228.0), start the web user interface (Use your internet explorer/firefox and type in the IP address of the M37 e.g. //192.168.100.110). Navigate to “Set Up” -> “Look Up Album Details” and start the look up process.

This search run might take up some time.

After the search run the picture of the cover can be found in the bottom left corner of the playback display and is visible while choosing the music and makes the searching of music even more intuitive.

It is also possible to add a cover picture manually to an existing album. Download your required coverart in jpg-format from the web, e.g. from Amazon or Google pictures. Change the name of the JPG to something meaningful – for example “ABBA\_Gold.JPG”. Copy in a first step this



file to the import folder\* of the M37.

Afterwards browse to the album for that you have provided the coverart picture, then to „Options“ and afterwards to „Edit Album Details.“ Select „Artwork“ and then „Edit“. Look for the jpg-file - here „ABBA\_Gold.jpg“ - and store it.

You can as well add a picture to a piece of music at title level. The input is logically effected via the entry „Edit Track Details“.



\*You reach the „Import“ folder from your PC by entering the IP address of the M37, e.g. via the „run“ command, as follows: [\\192.168.100.110](http://192.168.100.110). In this way you get the folder structure of the M37. Please enter „revox“ for username as well as for password.